

SV240-297
Environment Test Report

Test Start : 2023,5,25
Test End : 2023,6,29

Tested by:

Chain Yang

Approved by:

Danny TC Chen

Ver 1.3

June 29, 2023

1. LOW TEMPERATURE/HUMIDITY OPERATING TEST(PASS)	2
2. HIGH TEMPERATURE/HUMIDITY OPERATING TEST(PASS)	5
3. LOW TEMPERATURE NON-OPERATING TEST(PASS)	7
4. HIGH TEMPERATURE NON-OPERATING TEST(PASS)	9
5. COLD START TEST(PASS)	11

1. Low Temperature/Humidity Operating Test(PASS)

1.1 Testing Objective

To meet the varied temperature requirements from the different areas because products may be subjected to varied operation temperature condition. The product must be tested to verify its temperature endurance.

1.2 Testing Procedure

1. Inspect the component (DUT) to establish operation pretest criteria and physical condition.
2. Connect the component (DUT) to the motherboard and verify its functionality for baseline.
3. Put the component (DUT) into chamber and the motherboard is outside then power on the motherboard.
4. Program the test profile and turn on the chamber based on specification.
5. Inspect the component (DUT) and compare it to pretest data and physical condition.
If any physical issue or malfunction happened during the testing ,this should be recorded and reported.

1.3 Testing Component (DUT)

1pc SV240-297 FIPS140 -2



1.4 Testing Equipment

KSON THS-A6T-150 Temperature/Humidity chamber



1.5 Testing Software

Running PassMark Burn-In Test Tool V8.1 Pro

1.6 Testing Location

Apacer QT Reliability & Environment Test Lab

1.7 Testing Specification

Operating Test

Test Item	Temperature (°C)	Humidity (%)	Time	Remark
Function Test	25	50	10 minutes	-
Function Test	25->20	50->5	2 hours	-
Function Test	20	5	2 hours	-
Function Test	20->-40	5->-	1 hour	-
Function Test	-40	-	96 hours	-
Function Test	-40->25	-->50	1hour 5minutes	-
Function Test	25	50	2 hours	-

1.8 Testing Criteria

1. Function works normally.
2. No crack on soldering, components.
3. No deformity on components.
4. No rust on metal parts.

1.9 Testing Result

Testing Condition	Temperature	Testing Time	Result	Remark
			Sample No. 1	
Operation	-40°C	96 hours	Pass	-

1.10 Testing Photo



2. High Temperature/Humidity Operating Test(PASS)

2.1 Testing Objective

To meet the varied temperature requirements from the different areas because products may be subjected to varied operation temperature condition. The product must be tested to verify its temperature endurance.

2.2 Testing Procedure

1. Inspect the component (DUT) to establish operation pretest criteria and physical condition.
2. Connect the component (DUT) to the motherboard and verify its functionality for baseline.
3. Put the component (DUT) into chamber and the motherboard is outside then power on the motherboard.
4. Program the test profile and turn on the chamber based on specification.
5. Inspect the component (DUT) and compare it to pretest data and physical condition.
If any physical issue or malfunction happened during the testing ,this should be recorded and reported.

2.3 Testing Component (DUT)

1pc SV240-297

2.4 Testing Equipment

KSON THS-A6T-150 Temperature/Humidity chamber



2.5 Testing Software

Running PassMark Burn-In Test Tool V8.1 Pro

2.6 Testing Location

Apacer QT Reliability & Environment Test Lab

2.7 Testing Specification

Operating Test

Test Item	Temperature (°C)	Humidity (%)	Time	Remark
Function Test	25	50	10 minutes	-
Function Test	25->85	50	2 hours	-
Function Test	85	50	94 hours	-
Function Test	85	50->95	2 hours	-
Function Test	85	95	2 hours	-
Function Test	85->25	95->50	2 hours	-
Function Test	25	50	2 hours	-

2.8 Testing Criteria

1. Function works normally.
2. No crack on soldering, components.
3. No deformity on components.
4. No rust on metal parts.

2.9 Testing Result

Testing Condition	Temperature/Humidity	Testing Time	Result	Remark
			Sample No. 1	
Operation	85°C/50~95%RH	96 hours	Pass	-

2.10 Testing Photo



3. Low Temperature Non-Operating Test(PASS)

3.1 Testing Objective

To meet the varied temperature requirements from the different areas because products may be subjected to varied operation temperature condition. The product must be tested to verify its temperature endurance.

3.2 Testing Procedure

1. Inspect the component (DUT) to establish operation pretest criteria and physical condition.
2. Put the component (DUT) into chamber and the motherboard is outside.
3. Program the test profile and turn on the chamber based on specification.
4. After test, inspect the component (DUT) and compare it to pretest data and physical condition.
If any physical issue or malfunction happened, this should be recorded and reported.

3.3 Testing Component (DUT)

1pc SV240-297

3.4 Testing Equipment

KSON THS-A6T-150 Temperature/Humidity chamber



3.5 Testing Software

Running PassMark Burn-In Test Tool V8.1 Pro

3.6 Testing Location

Apacer QT Reliability & Environment Test Lab

3.7 Testing Specification

Non-Operating Test

Test Item	Temperature (°C)	Time	Remark
System Off	25	10 minutes	-
System Off	25->-55	1 hour 20minutes	-
System Off	-55	96 hours	-
System Off	-55->25	1 hour 20minutes	-
System Off	25	2 hours	-

3.8 Testing Criteria

1. Function works normally.
2. No crack on soldering, components.
3. No deformity on components.
4. No rust on metal parts.

3.9 Testing Result

Testing Condition	Temperature	Testing Time	Result	Remark
			Sample No. 1	
Non-Operation	-55°C	96 hours	Pass	-

3.10 Testing Photo



4. High Temperature Non-Operating Test(PASS)

4.1 Testing Objective

To meet the varied temperature requirements from the different areas because products may be subjected to varied operation temperature condition. The product must be tested to verify its temperature endurance.

4.2 Testing Procedure

1. Inspect the component (DUT) to establish operation pretest criteria and physical condition.
2. Put the component (DUT) into chamber and the motherboard is outside.
3. Program the test profile and turn on the chamber based on specification.
4. After test, inspect the component (DUT) and compare it to pretest data and physical condition.
If any physical issue or malfunction happened, this should be recorded and reported.

4.3 Testing Component (DUT)

1pc SV240-297

4.4 Testing Equipment

KSON THS-A6T-150 Temperature/Humidity chamber



4.5 Testing Software

Running PassMark Burn-In Test Tool V8.1 Pro

4.6 Testing Location

Apacer QT Reliability & Environment Test Lab

4.7 Testing Specification

Non-Operating Test

Test Item	Temperature (°C)	Time	Remark
System Off	25	10 minutes	-
System Off	25->100	1 hour 15minutes	-
System Off	100	96 hours	-
System Off	100->25	1 hour 15minutes	-
System Off	25	2 hours	-

4.8 Testing Criteria

1. Function works normally.
2. No crack on soldering, components.
3. No deformity on components.
4. No rust on metal parts.

4.9 Testing Result

Testing Condition	Temperature	Testing Time	Result	Remark
			Sample No. 1	
Non-Operation	100°C	96 hours	Pass	-

4.10 Testing Photo



5. Cold Start Test(PASS)

5.1 Testing Objective

To meet the varied temperature requirements from the different areas because products may be subjected to varied operation temperature condition. The product must be tested to verify its cold start boot cycles.

5.2 Testing Procedure

1. Inspect the component (DUT) to establish operation pretest criteria and physical condition.
2. Connect the component (DUT) to the motherboard and verify its functionality for baseline.
3. Put the component (DUT) into chamber and the motherboard/Power Box are outside.
4. Program the test profile and turn on the chamber based on specification.
5. Power on the motherboard and run Passmark for 3 minutes then 2 minutes off.
6. Repeat step5 for another 99 times.
7. Keep the component (DUT) -40C and run Run-In C2I Test V1.8.6 for 60 minutes.
8. Ramp up to 85C in 45 minutes
9. Keep the component (DUT) running 60 minutes at 85C.
10. Ramp down to -40C at 1C/min
11. Repeat Step7 to Step10 for another 2 times
12. After the test, inspect the component (DUT) and compare it to pretest data and physical condition.
If any physical issue or malfunction happened during the testing ,this should be recorded and reported.

5.3 Testing Component (DUT)

1pc SV240-297

5.4 Testing Equipment

KSON THS-A6T-150 Temperature/Humidity chamber



5.5 Testing Software

Running Cold Start Test by Passmark and Power Box

5.6 Testing Location

Apacer QT Reliability & Environment Test Lab

5.7 Testing Specification

Operating Test

Test Item	Temperature (°C)	Time	Remark
System Off	25	5 minutes	-
System Off	25->-40	1 hour 5 minutes	-
Function Test	-40	3 minutes	repeat 100 times
System Off	-40	2 minutes	
System Off	-40->85	45 minutes	-
Function Test	85	3 minutes	repeat 100 times
System Off	85	2 minutes	
System Off	85->-40	45 minutes	-
Function Test	-40	60 minutes	repeat 3 times
Function Test	-40->85	45 minutes	
Function Test	85	60 minutes	
Function Test	85->-40	2 hours 5 minutes	
Function Test	-40->25	1 hour 5 minutes	-

5.8 Testing Criteria

1. Function works normally.
2. No crack on soldering, components.
3. No deformity on components.
4. No rust on metal parts.

5.9 Testing Result

Testing Condition	Temperature	Cycle	Result	Remark
			Sample No. 1	
Operation	-40°C	100 times	Pass	
	85°C	100 times	Pass	
	-40°C->85°C	3 times	Pass	

5.10 Testing Photo

