

***SV170-uSSD  
Environment Test Report***

**Test Start : 2019,1,14  
Test End : 2019,2,14**

**Tested by:**

**Chain Yang**

**Approved by:**

**Danny TC Chen**

**Ver 1.0**

**Feb. 14, 2019**

<b>1. LOW TEMPERATURE OPERATING TEST(PASS)</b>	<b>2</b>
<b>2. HIGH TEMPERATURE OPERATING TEST(PASS)</b>	<b>4</b>
<b>3. LOW TEMPERATURE NON-OPERATING TEST(PASS)</b>	<b>6</b>
<b>4. HIGH TEMPERATURE NON-OPERATING TEST(PASS)</b>	<b>8</b>

## 1. Low Temperature Operating Test(PASS)

### 1.1 Testing Objective

To meet the varied temperature requirements from the different areas because products may be subjected to varied operation temperature condition. The product must be tested to verify its temperature endurance.

### 1.2 Testing Procedure

1. Inspect the component (DUT) to establish operation pretest criteria and physical condition.
2. Connect the component (DUT) to the motherboard and verify its functionality for baseline.
3. Put the component (DUT) into chamber and the motherboard is outside then power on the motherboard.
4. Program the test profile and turn on the chamber based on specification.
5. Inspect the component (DUT) and compare it to pretest data and physical condition.  
If any physical issue or malfunction happened during the testing ,this should be recorded and reported.

### 1.3 Testing Component (DUT)

1pc SV170-uSSD

### 1.4 Testing Equipment

KSON THS-A6T-150 Temperature/Humidity chamber



### 1.5 Testing Software

Running PassMark Burn-In Test Tool V8 Pro

### 1.6 Testing Location

Apacer QT Reliability & Environment Test Lab

## 1.7 Testing Specification

Operating Test

Test Item	Temperature (°C)	Time	Remark
Function Test	25	10 minutes	-
Function Test	25->0	25 minutes	-
Function Test	0	72 hours	-
Function Test	0->25	25 minutes	-
Function Test	25	2 hours	-

## 1.8 Testing Criteria

1. Function works normally.
2. No crack on soldering, components.
3. No deformity on components.
4. No rust on metal parts.

## 1.9 Testing Result

Testing Condition	Temperature	Testing Time	Result	Remark
			Sample No. 1	
Operation	0°C	72 hours	Pass	-

## 2. High Temperature Operating Test(PASS)

### 2.1 Testing Objective

To meet the varied temperature requirements from the different areas because products may be subjected to varied operation temperature condition. The product must be tested to verify its temperature endurance.

### 2.2 Testing Procedure

1. Inspect the component (DUT) to establish operation pretest criteria and physical condition.
2. Connect the component (DUT) to the motherboard and verify its functionality for baseline.
3. Put the component (DUT) into chamber and the motherboard is outside then power on the motherboard.
4. Program the test profile and turn on the chamber based on specification.
5. Inspect the component (DUT) and compare it to pretest data and physical condition.  
If any physical issue or malfunction happened during the testing ,this should be recorded and reported.

### 2.3 Testing Component (DUT)

1pc SV170-uSSD

### 2.4 Testing Equipment

KSON THS-A6T-150 Temperature/Humidity chamber



### 2.5 Testing Software

Running PassMark Burn-In Test Tool V8 Pro

### 2.6 Testing Location

Apacer QT Reliability & Environment Test Lab

## 2.7 Testing Specification

### Operating Test

Test Item	Temperature (°C)	Time	Remark
Function Test	25	10 minutes	-
Function Test	25->70	45 minutes	-
Function Test	70	72 hours	-
Function Test	70->25	45 minutes	-
Function Test	25	2 hours	-

## 2.8 Testing Criteria

1. Function works normally.
2. No crack on soldering, components.
3. No deformity on components.
4. No rust on metal parts.

## 2.9 Testing Result

Testing Condition	Temperature	Testing Time	Result	Remark
			Sample No. 1	
Operation	70°C	72 hours	Pass	-

### 3. Low Temperature Non-Operating Test(PASS)

#### 3.1 Testing Objective

To meet the varied temperature requirements from the different areas because products may be subjected to varied operation temperature condition. The product must be tested to verify its temperature endurance.

#### 3.2 Testing Procedure

1. Inspect the component (DUT) to establish operation pretest criteria and physical condition.
2. Connect the component (DUT) to the motherboard and verify its functionality for baseline.
3. Put the component (DUT) into chamber and the motherboard is outside then power on the motherboard.
4. Program the test profile and turn on the chamber based on specification.
5. Inspect the component (DUT) and compare it to pretest data and physical condition.  
If any physical issue or malfunction happened during the testing ,this should be recorded and reported.

#### 3.3 Testing Component (DUT)

1pc SV170-uSSD

#### 3.4 Testing Equipment

KSON THS-A6T-150 Temperature/Humidity chamber



#### 3.5 Testing Software

Running PassMark Burn-In Test Tool V8 Pro

#### 3.6 Testing Location

Apacer QT Reliability & Environment Test Lab

### 3.7 Testing Specification

Non-Operating Test

Test Item	Temperature (°C)	Time	Remark
System Off	25	10 minutes	-
System Off	25->-40	1 hour 5minutes	-
System Off	-40	72 hours	-
System Off	-40->25	1 hour 5minutes	-
System Off	25	2 hours	-

### 3.8 Testing Criteria

1. Function works normally.
2. No crack on soldering, components.
3. No deformity on components.
4. No rust on metal parts.

### 3.9 Testing Result

Testing Condition	Temperature	Testing Time	Result	Remark
			Sample No. 1	
Non-Operation	-40°C	72 hours	Pass	-

## 4. High Temperature Non-Operating Test(PASS)

### 4.1 Testing Objective

To meet the varied temperature requirements from the different areas because products may be subjected to varied operation temperature condition. The product must be tested to verify its temperature endurance.

### 4.2 Testing Procedure

1. Inspect the component (DUT) to establish operation pretest criteria and physical condition.
2. Connect the component (DUT) to the motherboard and verify its functionality for baseline.
3. Put the component (DUT) into chamber and the motherboard is outside then power on the motherboard.
4. Program the test profile and turn on the chamber based on specification.
5. Inspect the component (DUT) and compare it to pretest data and physical condition.  
If any physical issue or malfunction happened during the testing ,this should be recorded and reported.

### 4.3 Testing Component (DUT)

1pc SV170-uSSD

### 4.4 Testing Equipment

KSON THS-A6T-150 Temperature/Humidity chamber



### 4.5 Testing Software

Running PassMark Burn-In Test Tool V8 Pro

### 4.6 Testing Location

Apacer QT Reliability & Environment Test Lab

## 4.7 Testing Specification

Non-Operating Test

Test Item	Temperature (°C)	Time	Remark
System Off	25	10 minutes	-
System Off	25->85	1 hour	-
System Off	85	72 hours	-
System Off	85->25	1 hour	-
System Off	25	2 hours	-

## 4.8 Testing Criteria

1. Function works normally.
2. No crack on soldering, components.
3. No deformity on components.
4. No rust on metal parts.

## 4.9 Testing Result

Testing Condition	Temperature	Testing Time	Result	Remark
			Sample No. 1	
Non-Operation	85°C	72 hours	Pass	-